



TANGENT KNOCKOUT
(DIMENSION ON DRAWING TO
CENTERLINE OF "A" KNOCKOUT)

WIRING DIAGRAMS	
FUSIBLE	NOT FUSIBLE
A B	C

TERMINAL LUGS			
AMPERES	MAX WIRE	MIN WIRE	TYPE
30	#6 AWG	#14 AWG	AL OR CU

KNOCKOUTS				
SYMBOL	CONDUIT SIZE		DIAMETER	
	IN	MM	IN	MM
A	.50	13	.88	22
B	.75	19	1.13	29
C	1.00	25	1.38	35
D	1.25	32	1.75	44

NEMA TYPE 1

SEISMIC NOTES:
USE (4) 1/4" DIA GRADE 5 STEEL MOUNTING BOLTS @ HOLES AA
MAX CONFIGURED WEIGHT 10 LB FOR THE PURPOSE OF DETERMINING
SEISMIC ANCHORAGE REQUIREMENTS. FOR ALL OTHER APPLICATIONS,
CONTACT SQUARE D COMPANY.

*DIMENSIONS TO BOX (NOT COVER)

DUAL DIMENSIONS: INCHES
MILLIMETERS

Catalog Number	Voltage Ratings	Amperage Ratings	Wiring Diag	Horsepower Ratings																	
				240VAC				480VAC				600VAC				250 VDC	600 VDC				
				STD		MAX		STD		MAX		STD		MAX							
				1 ϕ	3 ϕ	1 ϕ	3 ϕ	1 ϕ	3 ϕ	1 ϕ	3 ϕ	1 ϕ	3 ϕ	1 ϕ	3 ϕ						
				1 1/2 $\bullet$	3 $\nmid$	3 $\bullet$	7 1/2 $\nmid$	—	—	—	—	—	—	—	—	—	5 $\blacktriangle$	—	—	—	
H321N	240VAC,250VDC	30	B	1 1/2 $\blacktriangle$	3 $\nmid$	3 $\blacktriangle$	7 1/2 $\nmid$	—	—	—	—	—	—	—	—	—	—	5 $\blacktriangle$	—	—	—
H361	600VAC,600VDC	30	B	—	—	—	—	3 $\blacktriangle$	5 $\blacksquare$	7 1/2 $\blacktriangle$	15 $\blacksquare$	—	7 1/2	—	20	5 $\blacktriangle$	—	10 $\blacktriangle$	15	—	
H361N	600VAC,600VDC	30	B	—	—	—	—	3 $\blacktriangle$	5 $\nmid$	7 1/2 $\blacktriangle$	15 $\nmid$	—	7 1/2	—	20	5 $\blacktriangle$	—	10 $\blacktriangle$	15	—	
HU361	600VAC,600VDC	30	C	—	—	5 $\blacktriangle$	10 $\blacksquare$	—	—	7 1/2 $\blacktriangle$	20 $\blacksquare$	—	—	10 $\blacktriangle$	30	—	5 $\blacktriangle$	—	15	—	
HU361EI	600VAC,600VDC	30	C	—	—	5 $\blacktriangle$	10 $\blacksquare$	—	—	7 1/2 $\blacktriangle$	20 $\blacksquare$	—	—	10 $\blacktriangle$	30	—	5 $\blacktriangle$	—	15	—	

NOTES:	HU361	600VAC,600
UL LISTED - E2875	HU361EI	600VAC,600
FINISH - GRAY BAKED ENAMEL		
▲ ALL NEUTRALS - INSULATED		
▲ USE BOTH OUTER SWITCHING POLES		
▲ USE BOTH SWITCHING POLES		
▲ IF CORNER GROUNDED DELTA, INSTALL NEUTRAL AND USE OUTER SWITCHING POLES		
FOR UNGROUNDED CONDUCTORS.		
▲ FOR CORNER GROUNDED DELTA ONLY, USE OUTER SWITCHING POLES FOR UNGROUNDED CONDUCTORS.		

HEAVY DUTY SAFETY SWITCHES - SEISMIC
VISIBLE BLADE TYPE
30 AMPERE
ENCLOSURE - NEMA TYPE 1 GENERAL PURPOSE



SQUARE D
Schneider Electric

DWG# 2228S