



Main

Product or component type	Contactator
Range of product	8502S
Control circuit	Separate control circuit
[Uc] control circuit voltage	110 V AC 50 Hz 120 V AC 60 Hz
Contactator application	Non-reversing
Line Rated Current	135 A
Poles description	3P
Phase	3 phases
Rated power in HP	40 HP 200 V AC 50 HP 230 V AC 100 HP 460 V AC 100 HP 575 V AC
System Voltage	600 V AC
Control type	No control units
Local signalling	No indicator
Auxiliary contact composition	Without
Provided equipment	Fuse not supplied
Electrical connection	Screw clamp terminals
NEMA degree of protection	NEMA 1 painted sheet steel
Product certifications	CSA UL listed
NEMA size	4
Height	25.16 in (639 mm)
Depth	9.02 in (229 mm)
Width	11.26 in (286 mm)

Complementary

Environment

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 1545 - Schneider Electric declaration of conformity	Compliant - since 1545 - Schneider Electric declaration of conformity
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.