



Main

Product or component type	Receptacle Switch
Product destination	Plug ACP1034CD Appleton Powertite
Line Rated Current	100 A
NEMA degree of protection	NEMA 1 sheet steel
Motor power hp	60 hp 480 V AC 75 hp 600 V AC
Disconnecter device type	Fusible disconnect switch
Short-circuit current	10 kA <= 200 kA
Device mounting	Surface
Number of poles	3
Phase	3 phases
Electrical connection	Receptacle
Product certifications	UL listed
System Voltage	250 V DC 600 V AC
AWG gauge	AWG 14...AWG 1/0 (copper) AWG 12...AWG 1/0 (aluminium)
Wiring configuration	4-wire

Complementary

Environment

Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 1313 - Schneider Electric declaration of conformity	Compliant - since 1313 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.