

















Remote Transformers



Remote transformers install in an accessible location behind the ceiling or wall. For technical information on remote transformers, see pp. 592-593. Requires canopy (p. 469) or special power feed (pp. 474-475).

INPUT VOLTAGE OUTPUT VOLTAGE WATTAGE TYPE	ITEM NUMBER	COMPATIBLE DIMMER TYPE	COMPATIBLE DIMMING COIL	PLUG-IN TRANSFORMER OPTION INCLUDES 16' CORD	RECESSED REMOTE TRANSFORMER OPTION*	277 VOLT INPUT OPTION
--	-------------	---------------------------	----------------------------	---	---	--------------------------

SINGLE-FEED OPTIONS

 LED		1 X 120V 12V 1 X 60 WATTS** ELECTRONIC AC	700AT060EL	LOW-VOLTAGE ELECTRONIC 450 WATTS	—	—	—
 LED		1 X 120V 12V 1 X 75 WATTS** MAGNETIC AC	700AT075T	LOW-VOLTAGE MAGNETIC 600 WATTS	—	700AT075P	700AT075T277
 LED		1 X 120V 12V 1 X 150 WATTS** MAGNETIC AC	700AT150T	LOW-VOLTAGE MAGNETIC 600 WATTS	700DIM150 (P. 593)	700AT150P	700AT150T277
 LED		1 X 120V 12V 1 X 150 WATTS** ELECTRONIC DC	700AT152EL	LOW-VOLTAGE ELECTRONIC 600 WATTS	—	—	—
 LED		1 X 120V 12V 1 X 300 WATTS** MAGNETIC AC	700AT300T	LOW-VOLTAGE MAGNETIC 600 WATTS	700DIM300 (P. 593)	700AT300P	700AT300T277 700AT300TR277*
 LED		1 X 120V 12V 1 X 300 WATTS ELECTRONIC DC	700AT300EL	LOW-VOLTAGE ELECTRONIC 600 WATTS	—	700AT300ELP	—
 LED		1 X 120V 12V 1 X 300 WATTS** ELECTRONIC DC	700AT302EL	LOW-VOLTAGE ELECTRONIC 600 WATTS	—	—	—
		1 X 120V 24V 1 X 300 WATTS MAGNETIC AC	700AT3024T	LOW-VOLTAGE MAGNETIC 600 WATTS	700DIM300 (P. 593)	700AT3024P	700AT3024TR 700AT3024TR277*
		1 X 120V 24V 1 X 600 WATTS MAGNETIC AC	700AT6024T	LOW-VOLTAGE MAGNETIC 1000 WATTS	700DIM600 (P. 593)	700AT6024P	700AT6024TR 700AT6024TR277*

DUAL-FEED OPTIONS

 LED		1 X 120V 12V 2 X 300 WATTS** MAGNETIC AC	700AT600T	LOW-VOLTAGE MAGNETIC 1000 WATTS	700DIM600 (P. 593)	700AT600P	700AT600TR 700AT600TR277*
---	---	---	-----------	---------------------------------------	-----------------------	-----------	------------------------------

* IN-WALL RECESSED REMOTE TRANSFORMERS ALSO AVAILABLE FOR MAGNETIC 300 AND 600 WATT MODELS FOR USE IN APPLICATIONS WHERE A REMOTE TRANSFORMER IS DESIRED BUT THERE ISN'T ACCESS TO A REMOTE LOCATION. SEE WWW.TECHLIGHTING.COM FOR DIMENSIONS AND FURTHER DETAILS.



** AS A GENERAL RULE WHEN USING LED FIXTURES WE DO NOT RECOMMEND USING GREATER THAN 70% OF SPECIFIED MAXIMUM WATTAGE ON THE TRANSFORMER DUE TO INRUSH CURRENT. FOR ASSISTANCE, PLEASE CONTACT OUR TECHNICAL SUPPORT DEPARTMENT.



INDICATES WHICH TRANSFORMERS ARE COMPATIBLE WITH LED ELEMENTS