

Product data sheet

Characteristics

EZML116125

Branch unit, EZ Meter-Pak, 125A, 6 sockets, 120/240VAC, lever bypass, ringless, 800A busbar



Main

| | |
|-------------------------|--------------------------|
| Product | Meter Center Branch Unit |
| Current Rating | 125 A |
| Type | Meter-Pak |
| Bus Rating | 800 A |
| Number of Jaws | 5 with jaw release |
| Number of Meter Sockets | 6 |
| Bypass Type | Lever bypass |
| Socket Type | Ringless |

Complementary

| | |
|------------------------|---------------------------|
| Busbar Material | Aluminium: busbar |
| Short-circuit current | 10 kA |
| Enclosure Rating | NEMA 3R |
| Maximum Voltage Rating | 120/240 V AC |
| Mounting | Surface |
| Phase | 1 phase in 1 phase out |
| Wire Configuration | 3-wire |
| Height | 75 in (1905.00 mm) |
| Width | 15.38 in (390.65 mm) |
| Depth | 8.95 in (227.33 mm) |

Ordering and shipping details

| | |
|-------------------|--------------------|
| Category | 00020-EZ METER-PAK |
| Discount Schedule | DE4 |
| GTIN | 785901068167 |
| Returnability | Yes |
| Country of origin | MX |

Packing Units

| | |
|------------------------------|-----------------------|
| Unit Type of Package 1 | PCE |
| Number of Units in Package 1 | 1 |
| Package 1 Height | 8.94 in (22.7 cm) |
| Package 1 Width | 15.35 in (39 cm) |
| Package 1 Length | 75.04 in (190.6 cm) |
| Package 1 Weight | 180.78 lb(US) (82 kg) |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.