


FEATURES

- Designed for concise control of each circuit
- Provides two separate 20 Amp circuits
- Track comes in 4', 8' and 12' lengths
- Structural channel is extruded aluminum
- Finishes: White (P) and Black (MB)

Compliances may not apply to all product configurations. Please consult the product spec sheet for compliance details.

COMPLIANCES: UL/cUL Listed, CSA Listed



TWO-CIRCUIT
POWER-TRAC

	L	W	H
L641 4' Nominal	42-5/8" [1083mm]	1-3/8" [35mm]	11/16" [18mm]
L642 8' Nominal	90-5/8" [2302mm]	1-3/8" [35mm]	11/16" [18mm]
L643 12' Nominal	138-5/8" [3521mm]	1-3/8" [35mm]	11/16" [18mm]

ORDERING INFORMATION

SAMPLE NUMBER: L641P

Track	Finishes	Connectors (Order Separately)	Accessories	Current Limiters (Order Separately)
L641 =4' Halo-2 Two Circuit Track L642 =8' Halo-2 Two Circuit Track L643 =12' Halo-2 Two Circuit Track	MB =Black P =White	L900 =Outlet Box Cover L941 =Live End Connector L942 =Flexible Connector L943 =Straight/"L" Connector L945L =Left "T" Connector L945R =Right "T" Connector L946 = "X" Connector L947 =Conduit Connector L949 =Mini Joiner L980 =Live End Conduit Adapter L989 =Conduit Continuation Kit Finishes MB =Black P =White	DE641 =Dead End L18 =18" Steel Stem L36 =36" Steel Stem L48 =48" Steel Stem L951 =Wire Way Cover for Pendant Assembly Kit L983 =T-Bar Attachment Clip L992 =Pendant Kit assembly L994 =Pendant Adapter Finishes MB =Black P =White	Current Limiter-Center Feed LC943 =LC943 Circuit 1 Breaker *CB1 =Circuit 1 Breaker LC943CB1200 =1200W (10A @ 120V) Circuit 2 Breaker *CB2 =Circuit 2 Breaker LC943CB120 =120W (1A @ 120V) LC943CB300 =300W (2.5A @ 120V) LC943CB600 =600W (5A @ 120V) LC943CB960 =960W (8A @ 120V) Finishes MB =Black P =White
				Current Limiter-End Feed Circuit 1 Breaker *CB1 =Circuit 1 Breaker LC941CB120 =120W (1A @ 120V) Circuit 2 Breaker *CB2 =Circuit 2 Breaker LC941CB1200 =1200W (10A @ 120V) LC941CB300 =300W (2.5A @ 120V) LC941CB600 =600W (5A @ 120V) LC941CB960 =960W (8A @ 120V) Finishes MB =Black P =White

CONNECTORS AND ACCESSORIES



L900 Outlet Box Cover



L929 Floating Canopy and Connector



L941 Live End Connector



L942 Flex Joiner



L943 Straight/L Connector



L945R Right T Connector



L945L Left T Connector



L946 X Connector



L947 Conduit Connector



L949 Mini Joiner



L951 Wire Way Cover for Pendant Assembly Kit



L983 T-Bar Attachment Clip



LC941 Current Limiter



L989 Conduit Continuation Kit



L992 Pendant Kit Assembly



DE641 Dead End



L994 45° Pendant Adapter

Specifications and dimensions subject to change without notice. Consult your Cooper Lighting Solutions Representative or visit www.cooperlighting.com for available options, accessories and ordering information.