

Job Name:		Item Number:	
Specifier Name:		Sales Agency:	
Specifier Contact:		Agency Contact:	
Fixture Type:		Comments:	
Quantity:		Approval:	

30w 12V Zero-Load Plug-In Transformer



Description

Transformer consumes 1-1.5 watts. Includes on/off switch and 8' output cord for connection to first LED Disk Light in a row or optional connection hub.

Specifications

Item Number	98640S-12
Finish	Black
Dimensions	L: 3 5/16" W: 1 1/2" H: 1 1/4"
Wire / Cord	96" (color/Black)
Switch Type	On/Off Switch
Connection	Plug Into Box
Safety Listing	cETL Listed for Damp Locations
Warranty	1-Year Warranty

Instruction Sheets

- English (HC-1887FS)

Shipping Information:

Package Type	Product #	Quantity	UPC	Length	Width	Height	Cube	Weight	UPS Ship
Individual	98640S-12	1	785652153235	4.75	2	2.625	0.014	0.3	Yes
Master Pack	98640S-12	3	10785652153232	5.75	5.375	3.125	0.056	0.9	Yes
Shipping Master		30	20785652153239	15.625	11	7.125	0.709	9.8	Yes

Component Diagram:



STEP 1

Choose LED Disks
Select number of disks, housing color and color temperature needed for your project.



STEP 2

Select Connectors & Accessories
Order connection hubs, additional connector cords, extra cord mounting clips, wiring compartments and fused plugs needed for your installation. (Each disk includes a 36" linking cable.)



STEP 3

Select Transformers
Multiply the number of disks in your system by 4 watts to determine transformer size needed. LED disks are 12V AC for use with 12V power supplies.



7400 Linder Ave. | Skokie, Illinois 60077 | 800-347-5483
© 2013 Sea Gull Lighting LLC, a Generation Brands Company.